

Table 14.4.3.2 Testing

Component	Initial Acceptance	Periodic Frequency	Method
1. All equipment	X	See Table 14.3.1.	
2. Control equipment and transponder			
(1) Functions	X	Annually	Verify correct receipt of alarm, supervisory, and trouble signals (inputs); operation of evacuation signals and auxiliary functions (outputs); circuit supervision, including detection of open circuits and ground faults; and power supply supervision for detection of loss of ac power and disconnection of secondary batteries.
(2) Fuses	X	Annually	Verify rating and supervision.
(3) Interfaced equipment	X	Annually	Verify integrity of single or multiple circuits providing interface between two or more control units. Test interfaced equipment connections by operating or simulating operation of the equipment being supervised. Verify signals required to be transmitted at the control unit.
(4) Lamps and LEDs	X	Annually	Illuminate lamps and LEDs.
(5) Primary (main) power supply	X	Annually	Disconnect all secondary (standby) power and test under maximum load, including all alarm appliances requiring simultaneous operation. Reconnect all secondary (standby) power at end of test. Test redundant power supplies separately.
3. Alarm control unit trouble signals			
(1) Audible and visual	X	Annually	Verify operation of control unit trouble signals. Verify ring-back feature for systems using a trouble-silencing switch that requires resetting.
(2) Disconnect switches	X	Annually	If control unit has disconnect or isolating switches, verify performance of intended function of each switch. Verify receipt of trouble signal when a supervised function is disconnected.
(3) Ground-fault monitoring circuit	X	Annually	If the system has a ground detection feature, verify the occurrence of ground-fault indication whenever any installation conductor is grounded.
(4) Transmission of signals to off-premises location	X	Annually	<p>Actuate an initiating device and verify receipt of alarm signal at the off-premises location.</p> <p>Create a trouble condition and verify receipt of a trouble signal at the off-premises location.</p> <p>Actuate a supervisory device and verify receipt of a supervisory signal at the off-premises location. If a transmission carrier is capable of operation under a single- or multiple-fault condition, actuate an initiating device during such fault condition and verify receipt of an alarm signal and a trouble signal at the off-premises location.</p>
4. Supervising station alarm systems — transmission equipment			
(1) All equipment	X	Annually	<p>^aTest all system functions and features in accordance with the equipment manufacturer's published instructions for correct operation in conformance with the applicable sections of Chapter 26.</p> <p>Except for DACT, actuate initiating device and verify receipt of the correct initiating device signal at the supervising station within 90 seconds. Upon completion of the test, restore the system to its functional operating condition.</p> <p>If test jacks are used, conduct the first and last tests without the use of the test jack.</p>

Component	Initial Acceptance	Periodic Frequency	Method
(2) Digital alarm communicator transmitter (DACT)	X	Annually	<p>Except for DACTs installed prior to adoption of the 2013 edition of NFPA 72 that are connected to a telephone line (number) that is also supervised for adverse conditions by a derived local channel, ensure connection of the DACT to two separate means of transmission.</p> <p>Test DACT for line seizure capability by initiating a signal while using the telephone line (primary line for DACTs using two telephone lines) for a telephone call. Ensure that the call is interrupted and that the communicator connects to the digital alarm receiver. Verify receipt of the correct signal at the supervising station. Verify each transmission attempt is completed within 90 seconds from going off-hook to on-hook.</p> <p>Disconnect the telephone line (primary line for DACTs using two telephone lines) from the DACT. Verify indication of the DACT trouble signal occurs at the premises fire alarm control unit within 4 minutes of detection of the fault. Verify receipt of the telephone line trouble signal at the supervising station. Restore the telephone line (primary line for DACTs using two telephone lines), reset the fire alarm control unit, and verify that the telephone line fault trouble signal returns to normal. Verify that the supervising station receives the restoral signal from the DACT.</p> <p>Disconnect the secondary means of transmission from the DACT. Verify indication of the DACT trouble signal occurs at the premises fire alarm control unit within 4 minutes of detection of the fault. Verify receipt of the secondary means trouble signal at the supervising station. Restore the secondary means of transmission, reset the fire alarm control unit, and verify that the trouble signal returns to normal. Verify that the supervising station receives the restoral signal from the secondary transmitter.</p> <p>Cause the DACT to transmit a signal to the DACR while a fault in the telephone line (number) (primary line for DACTs using two telephone lines) is simulated. Verify utilization of the secondary communications path by the DACT to complete the transmission to the DACR.</p>
(3) Digital alarm radio transmitter (DART)	X	Annually	<p>Disconnect the primary telephone line. Verify transmission of a trouble signal to the supervising station by the DART occurs within 4 minutes.</p>
(4) McCulloh transmitter	X	Annually	<p>Actuate initiating device. Verify production of not less than three complete rounds of not less than three signal impulses each by the McCulloh transmitter.</p> <p>If end-to-end metallic continuity is present and with a balanced circuit, cause each of the following four transmission channel fault conditions in turn, and verify receipt of correct signals at the supervising station:</p> <ol style="list-style-type: none"> (1) Open (2) Ground (3) Wire-to-wire short (4) Open and ground <p>If end-to-end metallic continuity is not present and with a properly balanced circuit, cause each of the following three transmission channel fault conditions in turn, and verify receipt of correct signals at the supervising station:</p> <ol style="list-style-type: none"> (1) Open (2) Ground (3) Wire-to-wire short

Component	Initial Acceptance	Periodic Frequency	Method
(5) Radio alarm transmitter (RAT)	X	Annually	Cause a fault between elements of the transmitting equipment. Verify indication of the fault at the protected premises, or transmission of trouble signal to the supervising station.
(6) Performance-based technologies	X	Annually	<p>Perform tests to ensure the monitoring of integrity of the transmission technology and technology path. Where shared communications equipment is used as permitted by 26.6.3.1.14, provided secondary (standby) power sources shall be tested in accordance with Table 14.4.3.2, item 7, 8, or 9, as applicable.</p> <p>Where a single communications path is used, disconnect the communication path. Manually initiate an alarm signal transmission or allow the check-in (handshake) signal to be transmitted automatically. ^bVerify the premises unit annunciates the failure within 200 seconds of the transmission failure. Restore the communication path.</p> <p>Where multiple communication paths are used, disconnect both communication paths. Manually initiate an alarm signal transmission. Verify the premises control unit annunciates the failure within 200 seconds of the transmission failure. Restore both communication paths.</p>
5. Emergency communications equipment			
(1) Amplifier/tone generators	X	Annually	Verify correct switching and operation of backup equipment.
(2) Call-in signal silence	X	Annually	Operate/function and verify receipt of correct visual and audible signals at control unit.
(3) Off-hook indicator (ring down)	X	Annually	Install phone set or remove phone from hook and verify receipt of signal at control unit.
(4) Phone jacks	X	Annually	Visually inspect phone jack and initiate communications path through jack.
(5) Phone set	X	Annually	Actuate each phone set and verify correct operation.
(6) System performance	X	Annually	Operate the system with a minimum of any five handsets simultaneously. Verify voice quality and clarity.
6. Engine-driven generator	X	Monthly	If an engine-driven generator dedicated to the system is used as a required power source, verify operation of the generator and transfer switch in accordance with NFPA 110 by the building owner.
7. Energy storage systems (ESS)	X	Annually	If an ESS system dedicated to the system is used as a required power source, verify by the building owner operation of the ESS system in accordance with NFPA 111.
8. Secondary (standby) power supply ^c	X	Annually	Disconnect all primary (main) power supplies and verify the occurrence of required trouble indication for loss of primary power. Measure or verify the system's standby and alarm current demand using the equipment manufacturer's data and verify the battery's rated capacity exceeds the system's power demand, including the safety margin. Operate general alarm systems a minimum of 5 minutes and emergency voice communications systems for a minimum of 15 minutes. Reconnect primary (main) power supply at end of test.
9. VRLA battery and charger ^d			Prior to conducting any battery testing, verify by the person conducting the test, that all system software stored in volatile memory is protected from loss.
(1) Temperature test	X	Semiannually	Upon initially opening the cabinet door, measure and record the temperature of each battery cell/unit at the negative terminal with an infrared thermometer. Replace any battery cell/unit if the temperature is greater than 18°F (10°C) above ambient.

Component	Initial Acceptance	Periodic Frequency	Method
(2) Charger test ^f	X	Semiannually	With the battery fully charged and connected to the charger, measure the voltage across the battery with a voltmeter. Verify the voltage is within the battery/alarm equipment manufacturer's recommendations. If the voltage is outside of the specified limits, either adjust the charger to within limits or replace the charger.
(3) Cell/Unit voltage test	X	Semiannually	With the battery fully charged and connected to the charger, measure the voltage of each cell/unit with a voltmeter. Replace the battery when any cell/unit measures a voltage less than 13.26 volts.
(4) Ohmic test ^g	X	N/A	When the battery is installed, establish a baseline ohmic value for each battery cell/unit or where available use baseline ohmic values provided by the battery or test equipment manufacturer. In either case record the base line ohmic value on each battery cell/unit.
		Semiannually	With the battery fully charged and connected to the charger, measure the internal ohmic value of each battery cell/unit. Record the test date and ohmic value on each cell/unit. Replace the battery when the ohmic measurement of any cell/unit deviates from the established baseline by 30% or more for conductance and 40% or more for resistance or impedance. Where the battery or test equipment manufacturer's baseline ohmic values are used, replace the battery when any cell/unit has an internal ohmic value outside of the acceptable range.
(5) Replacement/Load test ^h		3 years	Replace the battery or conduct a load test of the battery capacity. Load test the battery based on the manufacturer's specifications for a discharge rate of 3 hours or more by applying the current indicated for the selected hourly discharge rate continuously, until the terminal voltage decreases to the end voltage specified by the manufacturer. Record the test duration and calculate the battery capacity including adjustment for ambient temperature. Replace the battery if capacity is less than or equal to 80% or at the next scheduled test interval if battery capacity is less than 85%.
10. Public emergency alarm reporting system — wired system	X	Daily	<p>Manual tests of the power supply for public reporting circuits shall be made and recorded at least once during each 24-hour period. Such tests shall include the following:</p> <p>(1) Current strength of each circuit. Changes in current of any circuit exceeding 10 percent shall be investigated immediately.</p> <p>(2) Voltage across terminals of each circuit inside of terminals of protective devices. Changes in voltage of any circuit exceeding 10 percent shall be investigated immediately.</p> <p>(3) Voltage between ground and circuits. If this test shows a reading in excess of 50 percent of that shown in the test specified in (2), the trouble shall be immediately located and cleared. Readings in excess of 25 percent shall be given early attention. These readings shall be taken with a calibrated voltmeter of not more than 100 ohms resistance per volt. Systems in which each circuit is supplied by an independent current source (Forms 3 and 4) require tests between ground and each side of each circuit. Common current source systems (Form 2) require voltage tests between ground and each terminal of each battery and other current source.</p> <p>(4) Ground current reading shall be permitted in lieu of (3). If this method of testing is used, all grounds showing a current reading in excess of 5 percent of the supplied line current shall be given immediate attention.</p> <p>(5) Voltage across terminals of common battery on switchboard side of fuses.</p> <p>(6) Voltage between common battery terminals and ground. Abnormal ground readings shall be investigated immediately.</p>

Component	Initial Acceptance	Periodic Frequency	Method
			Tests specified in (5) and (6) shall apply only to those systems using a common battery. If more than one common battery is used, each common battery shall be tested.
11. Remote annunciators	X	Annually	Verify the correct operation and identification of annunciators. If provided, verify the correct operation of annunciator under a fault condition.
12. Reserved			
13. Reserved			
14. Reserved			
15. Conductors — metallic			
(1) Stray voltage	X	N/A	Test all installation conductors with a volt/ohmmeter to verify that there are no stray (unwanted) voltages between installation conductors or between installation conductors and ground. Verify the maximum allowable stray voltage does not exceed 1 volt ac/dc, unless a different threshold is specified in the manufacturer's published instructions for the installed equipment.
(2) Ground faults	X	N/A	Test all installation conductors, other than those intentionally and permanently grounded, for isolation from ground per the installed equipment manufacturer's published instructions.
(3) Short-circuit faults	X	N/A	Test all installation conductors, other than those intentionally connected together, for conductor-to-conductor isolation per the manufacturer's published instructions for the installed equipment. Also test these same circuits conductor-to-ground.
(4) Loop resistance	X	N/A	With each initiating and indicating circuit installation conductor pair short-circuited at the far end, measure and record the resistance of each circuit. Verify that the loop resistance does not exceed the limits specified in the manufacturer's published instructions for the installed equipment.
(5) Circuit integrity	X	N/A	For initial and reacceptance testing, confirm the introduction of a fault in any circuit monitored for integrity results in a trouble indication at the fire alarm control unit. Open one connection at not less than 10 percent of the initiating devices, notification appliances and controlled devices on every initiating device circuit, notification appliance circuit, and signaling line circuit. Confirm all circuits perform as indicated in Sections 23.5, 23.6, and 23.7.
	N/A	Annually	For periodic testing, test each initiating device circuit, notification appliance circuit, and signaling line circuit for correct indication at the control unit. Confirm all circuits perform as indicated in Sections 23.5, 23.6, and 23.7.
16. Conductors — nonmetallic			
(1) Fiber optics	X	N/A	Test the fiber-optic transmission line by the use of an optical power meter or by an optical time domain reflectometer used to measure the relative power loss of the line. Test result data must meet or exceed ANSI/TIA 568-C.3, <i>Optical Fiber Cabling Components Standard</i> , related to fiber-optic lines and connection/splice losses and the control unit manufacturer's published specifications.
(2) Circuit integrity	X	N/A	For initial and reacceptance testing, confirm the introduction of a fault in any circuit monitored for integrity results in a trouble indication at the fire alarm control unit. Open one connection at not less than 10 percent of the initiating devices, notification appliances, and controlled devices on every initiating device circuit, notification appliance circuit, and signaling line circuit. Confirm all circuits perform as indicated in Sections 23.5, 23.6, and 23.7.

Component	Initial Acceptance	Periodic Frequency	Method
	N/A	Annually	For periodic testing, test each initiating device circuit, notification appliance circuit, and signaling line circuit for correct indication at the control unit. Confirm all circuits perform as indicated in Sections 23.5, 23.6, and 23.7.
17. Initiating devices ^l			
(1) Electromechanical releasing device			
(a) Nonrestorable-type link	X	Annually	Verify correct operation by removal of the fusible link and operation of the associated device.
(b) Restorable-type link ^k	X	Annually	Verify correct operation by removal of the fusible link and operation of the associated device.
(2) Fire extinguishing system(s) or suppression system(s) alarm switch	X	Annually	Operate the switch mechanically or electrically and verify receipt of signal by the fire alarm control unit.
(3) Fire-gas and other detectors	X	Annually	Test fire-gas detectors and other fire detectors as prescribed by the manufacturer and as necessary for the application.
(4) Heat detectors			
(a) Fixed-temperature, rate-of-rise, rate of compensation, restorable line, spot type (excluding pneumatic tube type)	X	Annually (see 14.4.4.5)	Perform heat test with a listed and labeled heat source or in accordance with the manufacturer's published instructions. Assure that the test method for the installed equipment does not damage the nonrestorable fixed-temperature element of a combination rate-of-rise/fixed-temperature element detector.
(b) Fixed-temperature, nonrestorable line type	X	Annually	Do not perform heat test. Test functionality mechanically and electrically. Measure and record loop resistance. Investigate changes from acceptance test.
(c) Fixed-temperature, nonrestorable spot type	X	See Method	After 15 years from initial installation, replace all devices or have 2 detectors per 100 laboratory tested. Replace the 2 detectors with new devices. If a failure occurs on any of the detectors removed, remove and test additional detectors to determine either a general problem involving faulty detectors or a localized problem involving 1 or 2 defective detectors. If detectors are tested instead of replaced, repeat tests at intervals of 5 years.
(d) Nonrestorable (general)	X	Annually	Do not perform heat tests. Test functionality mechanically and electrically.
(e) Restorable line type, pneumatic tube only	X	Annually	Perform heat tests (where test chambers are in circuit), with a listed and labeled heat source or in accordance with the manufacturer's published instructions of the detector or conduct a test with pressure pump.
(f) Single- and multiple-station heat alarms	X	Annually	Conduct functional tests according to manufacturer's published instructions. Do not test nonrestorable heat detectors with heat.
(5) Manual fire alarm boxes	X	Annually	Operate manual fire alarm boxes per the manufacturer's published instructions. Test both key-operated presignal and general alarm manual fire alarm boxes.
(6) Radiant energy fire detectors	X	Semiannually	Test flame detectors and spark/ember detectors in accordance with the manufacturer's published instructions to determine that each detector is operative. Determine flame detector and spark/ember detector sensitivity using any of the following: (1) Calibrated test method (2) Manufacturer's calibrated sensitivity test instrument (3) Listed control unit arranged for the purpose

Component	Initial Acceptance	Periodic Frequency	Method
(7) Smoke detectors — functional test		Annually	<p>(4) Other approved calibrated sensitivity test method that is directly proportional to the input signal from a fire, consistent with the detector listing or approval</p> <p>If designed to be field adjustable, replace detectors found to be outside of the approved range of sensitivity or adjust to bring them into the approved range.</p> <p>Do not determine flame detector and spark/ember detector sensitivity using a light source that administers an unmeasured quantity of radiation at an undefined distance from the detector.</p>
(a) In other than one- and two-family dwellings, system detectors	X	Annually	<p>^lTest smoke detectors in place to ensure smoke entry into the sensing chamber and an alarm response. Use smoke or a listed and labeled product acceptable to the manufacturer or in accordance with their published instructions. Other methods listed in the manufacturer's published instructions that ensure smoke entry from the protected area, through the vents, into the sensing chamber can be used.</p>
(b) Single- and multiple-station smoke alarms connected to protected premises systems	X	Annually	<p>Perform a functional test on all single- and multiple-station smoke alarms connected to a protected premises fire alarm system by putting the smoke alarm into an alarm condition.</p>
(c) System smoke detectors used in one- and two-family dwellings	X	Annually	<p>Conduct functional tests according to manufacturer's published instructions.</p>
(d) Air sampling	X	Annually	<p>Test with smoke or a listed and labeled product acceptable to the manufacturer or in accordance with their published instructions. Test from the end sampling port or point on each pipe run. Verify airflow through all other ports or points.</p>
(e) Duct type	X	Annually	<p>In addition to the testing required in Table 14.4.3.2(g)(1) and Table 14.4.3.2(h), test duct smoke detectors that use sampling tubes to ensure that they will properly sample the airstream in the duct using a method acceptable to the manufacturer or in accordance with their published instructions.</p>
(f) Projected beam type	X	Annually	<p>Test the detector by introducing smoke, other aerosol, or an optical filter into the beam path.</p>
(g) Smoke detector with built-in thermal element	X	Annually	<p>Operate both portions of the detector independently as described for the respective devices.</p>
(h) Smoke detectors with control output functions	X	Annually	<p>Verify that the control capability remains operable even if all of the initiating devices connected to the same initiating device circuit or signaling line circuit are in an alarm state.</p>
(8) Smoke detectors — sensitivity testing		See 14.4.4.3	<p>^mPerform any of the following tests to ensure that each smoke detector is within its listed and marked sensitivity range:</p> <ol style="list-style-type: none"> (1) Calibrated test method (2) Manufacturer's calibrated sensitivity test instrument (3) Listed control equipment arranged for the purpose (4) Smoke detector/control unit arrangement whereby the detector causes a signal at the control unit when its sensitivity is outside its listed sensitivity range (5) Other calibrated sensitivity test method approved by the authority having jurisdiction
In other than one- and two-family dwellings, system detectors	N/A	See 14.4.4.3	

Component	Initial Acceptance	Periodic Frequency	Method
(9) Carbon monoxide detectors/carbon monoxide alarms			
(a) CO entry test	X	Annually	Test the devices in place to ensure CO entry to the sensing chamber by introduction through the vents, to the sensing chamber of listed and labeled product acceptable to the manufacturer or in accordance with manufacturer's published instructions
(b) Air sampling	X	Annually	Per test methods documented in the manufacturer's published instructions, verify detector alarm response through the end sampling port on each pipe run; verify airflow through all other ports as well.
(c) Duct type	X	Annually	Test or inspect air duct detectors to ensure that the device will sample the airstream in accordance with the manufacturer's published instructions.
(d) CO detector with control output functions	X	Annually	Within each protected space, verify that the control capability remains operable even if all of the initiating devices connected to the same initiating device circuit or signaling line circuit are in an alarm state.
(10) Initiating devices, supervisory			
(a) Control valve switch	X	Semiannual	Operate valve and verify signal receipt to be within the first two revolutions of the handwheel or within one-fifth of the travel distance, or per the manufacturer's published instructions. Continue to cycle outside stem and yoke valves and verify switch does not reset during full travel of the valve stem.
(b) High- or low-air pressure switch	X	Annually	Operate switch and verify receipt of signal is obtained where the required pressure is increased or decreased a maximum 10 psi (70 kPa) from the required pressure level.
(c) Steam pressure	X	Annually	Operate switch and verify receipt of signal is obtained before pressure decreases to 110 percent of the minimum operating pressure of the steam-operated equipment.
(d) Pressure supervisory devices for other sources	X	Annually	Operate switch and verify receipt of signal is obtained where the required pressure is increased or decreased from the normal operating pressure by an amount specified in approved design documents.
(e) Room temperature switch	X	Annually	Operate switch and verify receipt of signal to indicate the decrease in room temperature to 40°F (4.4°C) and its restoration to above 40°F (4.4°C).
(f) Water level switch	X	Annually	Operate switch and verify receipt of signal indicating the water level raised or lowered a maximum 3 in. (70 mm) from the required level within a pressure tank, or a maximum 12 in. (300 mm) from the required level of a nonpressure tank. Also verify its restoral to required level.
(g) Water temperature switch	X	Annually	Operate switch and verify receipt of signal to indicate the decrease in water temperature to 40°F (4.4°C) and its restoration to above 40°F (4.4°C).
(11) Mechanical, electrosonic, or pressure-type waterflow device	X	Semiannually	Water shall be flowed through an inspector's test connection indicating the flow of water equal to that from a single sprinkler of the smallest orifice size installed in the system or other listed and approved waterflow switch test methods for wet-pipe systems, or an alarm test bypass connection for dry-pipe, pre-action, or deluge systems in accordance with NFPA 25.
(12) Multi-sensor fire detector or multi-criteria fire detector or combination fire detector	X	Annually	Test each of the detection principles present within the detector (e.g., smoke/heat/CO, etc.) independently for the specific detection principle, regardless of the configuration status at the time of testing. Also test each detector in accordance with the manufacturer's published instructions.

Component	Initial Acceptance	Periodic Frequency	Method
			<p>Test individual sensors together if the technology allows individual sensor responses to be verified.</p> <p>Perform tests as described for the respective devices by introduction of the physical phenomena to the sensing chamber of element. An electronic check (magnets, analog values, etc.) is not sufficient to comply with this requirement.</p> <p>Verify by using the detector manufacturer's published instructions that the test gas used will not impair the operation of either sensing chamber of a multisensor, multicriteria, or combination fire detector.</p> <p>Confirm the result of each sensor test through indication at the detector or control unit.</p> <p>Where individual sensors cannot be tested individually, test the primary sensor.ⁿ</p> <p>Record all tests and results.</p>
18. Special hazard equipment			
(1) Abort switch (dead-man type)	X	Annually	Operate abort switch and verify correct sequence and operation.
(2) Abort switch (recycle type)	X	Annually	Operate abort switch and verify development of correct matrix with each sensor operated.
(3) Abort switch (special type)	X	Annually	Operate abort switch and verify correct sequence and operation in accordance with authority having jurisdiction. Observe sequencing as specified on as-built drawings or in system owner's manual.
(4) Cross-zone detection circuit	X	Annually	Operate one sensor or detector on each zone. Verify occurrence of correct sequence with operation of first zone and then with operation of second zone.
(5) Matrix-type circuit	X	Annually	Operate all sensors in system. Verify development of correct matrix with each sensor operated.
(6) Release solenoid circuit ^o	X	Annually	Verify operation of solenoid.
(7) Squibb release circuit	X	Annually	Use AGI flashbulb or other test light approved by the manufacturer. Verify operation of flashbulb or light.
(8) Verified, sequential, or counting zone circuit	X	Annually	Operate required sensors at a minimum of four locations in circuit. Verify correct sequence with both the first and second detector in alarm.
(9) All above devices or circuits or combinations thereof	X	Annually	Verify supervision of circuits by creating an open circuit.
19. Combination systems			
(1) Fire extinguisher electronic monitoring device/system	X	Annually	Test communication between the device connecting the fire extinguisher electronic monitoring device/system and the fire alarm control unit to ensure proper signals are received at the fire alarm control unit and remote annunciator(s) if applicable.
(2) Carbon monoxide device/system	X	Annually	Test communication between the device connecting the carbon monoxide device/system and the fire alarm control unit to ensure proper signals are received at the fire alarm control unit and remote annunciator(s) if applicable.
20. Interface equipment ^p	X	See 14.4.4.4	Test interface equipment connections by operating or simulating the equipment being supervised. Verify signals required to be transmitted are received at the control unit. Test frequency for interface equipment is the same as the frequency required by the applicable NFPA standard(s) for the equipment being supervised.

Component	Initial Acceptance	Periodic Frequency	Method
21. Guard's tour equipment	X	Annually	Test the device in accordance with the manufacturer's published instructions.
22. Alarm notification appliances			
(1) Audible ^q	X	N/A	For initial and reacceptance testing, measure sound pressure levels for signals with a sound level meter meeting ANSI S1.4a, <i>Specifications for Sound Level Meters, Type 2</i> requirements. Measure sound pressure levels throughout the protected area to confirm that they are in compliance with Chapter 18. Set the sound level meter in accordance with ANSI/ASA S3.41, <i>American National Standard Audible Emergency Evacuation (E2) and Evacuation Signals with Relocation Instructions (ESRI)</i> , using the time-weighted characteristic F (FAST).
	N/A	Annually	For periodic testing, verify the operation of the notification appliances.
(2) Audible textual notification appliances (loudspeakers and other appliances to convey voice messages)	X	N/A	For initial and reacceptance testing, measure sound pressure levels for signals with a sound level meter meeting ANSI S1.4a, <i>Specifications for Sound Level Meters, Type 2</i> requirements. Measure sound pressure levels throughout the protected area to confirm that they are in compliance with Chapter 18. Set the sound level meter in accordance with ANSI/ASA S3.41, <i>American National Standard Audible Emergency Evacuation (E2) and Evacuation Signals with Relocation Instructions (ESRI)</i> , using the time-weighted characteristic F (FAST). Verify audible information to be intelligible and in compliance with 14.4.11.
	N/A	Annually	For periodic testing, verify the operation of the notification appliances.
(3) Visual	X	N/A	Perform initial and reacceptance testing in accordance with the manufacturer's published instructions. Verify appliance locations to be per approved layout and confirm that no floor plan changes affect the approved layout. Verify the candela rating or method of candela control marking on each visual appliance and rating when reported by the FACU agrees with the approved drawings. Confirm that each appliance flashes.
	N/A	Annually	For periodic testing, verify that each appliance flashes.
23. Exit marking audible notification appliance	X	Annually	Perform tests in accordance with manufacturer's published instructions.
24. Emergency control functions ^s	X	Annually	For initial, reacceptance, and periodic testing, verify emergency control function interface device activation. Where an emergency control function interface device is disabled or disconnected during initiating device testing, verify that the disabled or disconnected emergency control function interface device has been properly restored, including electromagnetic devices used for door releasing services as part of a fire alarm system.
25. Two-way emergency communications systems	X	Annually	Use the manufacturer's published instructions and the as-built drawings provided by the system supplier to verify correct operation after the initial testing phase has been performed by the supplier or by the supplier's designated representative. Test the two-way communication system to verify operation and receipt of visual and audible signals at the transmitting unit and the receiving unit, respectively. Operate systems with more than five stations with a minimum of five stations operating simultaneously. Verify voice quality and clarity.

Component	Initial Acceptance	Periodic Frequency	Method			
26. Special procedures			<p>Verify directions for the use of the two-way communication system, instructions for summoning assistance via the two-way communication system, and written identification of the location is posted adjacent to the two-way communication system.</p> <p>Verify that all remote stations are readily accessible.</p> <p>Verify the timed automatic communications capability to connect with a constantly attended monitoring location per 24.5.3.4.</p>			
(1) Alarm verification	X	Annually	<p>Verify time delay and alarm response for smoke detector circuits identified as having alarm verification.</p>			
(2) Multiplex systems	X	Annually	<p>Verify communications between sending and receiving units under both primary and secondary power.</p> <p>Verify communications between sending and receiving units under open-circuit and short-circuit trouble conditions.</p> <p>Verify communications between sending and receiving units in all directions where multiple communications pathways are provided.</p> <p>If redundant central control equipment is provided, verify switchover and all required functions and operations of secondary control equipment.</p> <p>Verify all system functions and features in accordance with manufacturer's published instructions.</p>			
27. Supervising station alarm systems — receiving equipment			<p>(1) All equipment</p>	X	Monthly	<p>Perform tests on all system functions and features in accordance with the equipment manufacturer's published instructions for correct operation in conformance with the applicable sections of Chapter 26.</p> <p>Actuate initiating device and verify receipt of the correct initiating device signal at the supervising station within 90 seconds. Upon completion of the test, restore the system to its functional operating condition.</p> <p>If test jacks are used, perform the first and last tests without the use of the test jack.</p>
(2) Digital alarm communicator receiver (DACR)	X	Monthly	<p>Disconnect each transmission means in turn from the DACR, and verify audible and visual annunciation of a trouble signal in the supervising station.</p> <p>Cause a signal to be transmitted on each individual incoming DACR line (path) at least once every 6 hours (24 hours for DACTs installed prior to adoption of the 2013 edition of <i>NFPA 72</i>). Verify receipt of these signals.</p>			
(3) Digital alarm radio receiver (DARR)	X	Monthly	<p>Cause the following conditions of all DARRs on all subsidiary and repeater station receiving equipment. Verify receipt at the supervising station of correct signals for each of the following conditions:</p> <ul style="list-style-type: none"> (1) AC power failure of the radio equipment (2) Receiver malfunction (3) Antenna and interconnecting cable failure (4) Indication of automatic switchover of the DARR (5) Data transmission line failure between the DARR and the supervising or subsidiary station 			

Component	Initial Acceptance	Periodic Frequency	Method
(4) McCulloh systems	X	Monthly	<p>Test and record the current on each circuit at each supervising and subsidiary station under the following conditions:</p> <p>(1) During functional operation</p> <p>(2) On each side of the circuit with the receiving equipment conditioned for an open circuit</p> <p>Cause a single break or ground condition on each transmission channel. If such a fault prevents the functioning of the circuit, verify receipt of a trouble signal.</p> <p>Cause each of the following conditions at each of the supervising or subsidiary stations and all repeater station radio transmitting and receiving equipment; verify receipt of correct signals at the supervising station:</p> <p>(1) RF transmitter in use (radiating)</p> <p>(2) AC power failure supplying the radio equipment</p> <p>(3) RF receiver malfunction</p> <p>(4) Indication of automatic switchover</p>
(5) Radio alarm supervising station receiver (RASSR) and radio alarm repeater station receiver (RARSR)	X	Monthly	<p>Cause each of the following conditions at each of the supervising or subsidiary stations and all repeater station radio transmitting and receiving equipment; verify receipt of correct signals at the supervising station:</p> <p>(1) AC power failure supplying the radio equipment</p> <p>(2) RF receiver malfunction</p> <p>(3) Indication of automatic switchover, if applicable</p>
(6) Private microwave radio systems	X	Monthly	<p>Cause each of the following conditions at each of the supervising or subsidiary stations and all repeater station radio transmitting and receiving equipment; verify receipt of correct signals at the supervising station:</p> <p>(1) RF transmitter in use (radiating)</p> <p>(2) AC power failure supplying the radio equipment</p> <p>(3) RF receiver malfunction</p> <p>(4) Indication of automatic switchover</p>
(7) Performance-based technologies	X	Monthly	<p>Perform tests to ensure the monitoring of integrity of the transmission technology and technology path. Where a single communications path is used, disconnect the communication path. Verify that failure of the path is annunciated at the supervising station within 60 minutes of the failure (within 5 minutes for communication equipment installed prior to adoption of the 2013 edition of <i>NFPA 72</i>). Restore the communication path. Where multiple communication paths are used, disconnect both communication paths and confirm that failure of the path is annunciated at the supervising station within not more than 6 hours of the failure (within 24 hours for communication equipment installed prior to adoption of the 2013 edition of <i>NFPA 72</i>). Restore both communication paths.</p>
28. Public emergency alarm reporting system transmission equipment			
(1) Publicly accessible alarm box	X	Semiannually	<p>Actuate publicly accessible initiating device(s) and verify receipt of not less than three complete rounds of signal impulses. Perform this test under normal circuit conditions. If the device is equipped for open circuit operation (ground return), test it in this condition as one of the semiannual tests.</p>

Component	Initial Acceptance	Periodic Frequency	Method
(2) Auxiliary box	X	Annually	Test each initiating circuit of the auxiliary box by actuation of a protected premises initiating device connected to that circuit. Verify receipt of not less than three complete rounds of signal impulses.
(3) Master box			
(a) Manual operation	X	Semiannually	Perform the tests prescribed for 28(a).
(b) Auxiliary operation	X	Annually	Perform the tests prescribed for 28(b).
29. Low-power radio (wireless systems)	X	N/A	<p>The following procedures describe additional acceptance and reacceptance test methods to verify wireless protection system operation:</p> <p>(1) Use the manufacturer's published instructions and the as-built drawings provided by the system supplier to verify correct operation after the initial testing phase has been performed by the supplier or by the supplier's designated representative.</p> <p>(2) Starting from the functional operating condition, initialize the system in accordance with the manufacturer's published instructions. Confirm the alternative communications path exists between the wireless control unit and peripheral devices used to establish initiation, indication, control, and annunciation. Test the system for both alarm and trouble conditions.</p> <p>(3) Check batteries for all components in the system monthly unless the control unit checks all batteries and all components daily.</p>
30. Mass notification systems			
(1) Functions	X	Annually	At a minimum, test control equipment to verify correct receipt of alarm, supervisory, and trouble signals (inputs); operation of evacuation signals and auxiliary functions (outputs); circuit supervision, including detection of open circuits and ground faults; and power supply supervision for detection of loss of ac power and disconnection of secondary batteries.
(2) Fuses	X	Annually	Verify the rating and supervision.
(3) Interfaced equipment	X	Annually	Verify integrity of single or multiple circuits providing interface between two or more control units. Test interfaced equipment connections by operating or simulating operation of the equipment being supervised. Verify signals required to be transmitted at the control unit.
(4) Lamps and LEDs	X	Annually	Illuminate lamps and LEDs.
(5) Primary (main) power supply	X	Annually	Disconnect all secondary (standby) power and test under maximum load, including all alarm appliances requiring simultaneous operation. Reconnect all secondary (standby) power at end of test. For redundant power supplies, test each separately.
(6) Audible textual notification appliances (loudspeakers and other appliances to convey voice messages)	X	Annually	<p>Measure sound pressure level with a sound level meter meeting ANSI S1.4a, <i>Specifications for Sound Level Meters, Type 2</i> requirements. Measure and record levels throughout protected area. Set the sound level meter in accordance with ANSI/ASA S3.41, <i>American National Standard Audible Emergency Evacuation Signal</i>, using the time-weighted characteristic F (FAST). Record the maximum output when the audible emergency evacuation signal is on.</p> <p>Verify audible information to be distinguishable and understandable.</p>

Component	Initial Acceptance	Periodic Frequency	Method
(7) Visual	X	Annually	Perform test in accordance with manufacturer's published instructions. Verify appliance locations to be per approved layout and confirm that no floor plan changes affect the approved layout. Verify the candela rating or method of candela control marking on each visual appliance and rating when reported by the FACU agrees with the approved drawings. Confirm that each appliance flashes.
(8) Control unit functions and no diagnostic failures are indicated	X	Annually	Review event log file and verify that the correct events were logged. Review system diagnostic log file; correct deficiencies noted in file. Delete unneeded log files. Delete unneeded error files. Verify that sufficient free disk space is available. Verify unobstructed flow of cooling air is available. Change/clean filters, cooling fans, and intake vents.
(9) Control unit reset	X	Annually	Power down the central control unit computer and restart it.
(10) Control unit security	X	Annually	If remote control software is loaded onto the system, verify that it is disabled to prevent unauthorized system access.
(11) Audible/visual functional test	X	Annually	Send out an alert to a diverse set of predesignated receiving devices and confirm receipt. Include at least one of each type of receiving device.
(12) Software backup	X	Annually	Make full system software backup. Rotate backups based on accepted practice at site.
(13) Secondary power test	X	Annually	Disconnect ac power. Verify the ac power failure alarm status on central control equipment. With ac power disconnected, verify battery voltage under load.
(14) Wireless signals	X	Annually	Check forward/reflected radio power is within specifications.
(15) Antenna	X	Annually	Check forward/reflected radio power is within specifications. Verify solid electrical connections with no observable corrosion.
(16) Transceivers	X	Annually	Verify proper operation and mounting is not compromised.